

LED Emergency Light ELD - 12



Function:

Emergency Lights are designed to provide Lights on Power Interruption. These Lights have built in

- * Battery (SMF Type),
- * Battery charger
- * Change over circuitry and
- * Inverter.

Till the mains is ON, the charger stores the energy in the battery. In the event of Power failure, the stored energy is used to light up the tubes.

Application:

To avoid accident and unwanted situations, these are must for

- * Industries,
- * Hotels,
- * Railways Stations, Air ports Theaters and
- * all Public Places.

Specifications:

Battery type	: SMF
	: Volt 12 V
	: Capacity 7 Ah
Lamp	: 1 Filament lamp 12V 36W in seal beam fitting
Charger	: Automatic- SMPS- CC/CV
Operation	: Automatic
Back-up Time	: 1.5 hours
Protections	: Battery- Over Charge
	: Battery- Deep Discharge
Indication	: Mains, Charging
Housing	: Steel Sheet with Powder Coated
Mounting	: Wall Mounting
Switches	: Test push & light Hi -OFF-LOW- Toggle switch
Size/weight	: (LxDxH) 205 mm x 170 mm x 300 mm/ 5kg



Pictures shown are for
illustration purpose only
Actual product may vary

MODEL NO. ELD-12

MRP. RS. 7,100/-

(incl. all Taxes and GST)



BAID POWER SERVICES Pvt. Ltd.

152, Block-B, Lake Town, Kolkata - 700089, West Bengal, India

Tel: +91(033)2521 0322, +91(033)2534 3662, +91(033)4067 8112

Email: info@indiapowerhouse.net, **Web: www.indiapowerhouse.com**